

## Features

### Features

- Neutral required
- Up to 200W
- Adjustable min. level and AUTO set max. level
- For LEDs, halogen lamps, INC
- Enable Wifi, works with Alexa/google assistant
- Trailing Edge



## Technical specification

Designation	Wifi light Dimmer
Part number	WRD-W
Soft start	YES
Input Voltage	220-240V / 50Hz
Dimming control	Can be controlled using Rotate .App via Wifi.and Voice control
Level Memory	Remembers the last set brightness level
Power range @230V	150W LED / CFL, 200W INC
Work with	Dimmable lamps and LED Driver
Dimming range	1-100%
Dimensions(L*W*H)(mm)	85*85*45

## Setting Min/Max level

- In order to better control the lighting, start to use this dimmer, there requires to setting the Min. /Max. level. Keep Press the button for 10S, the lights flashes 1 time, enter to the setting mode.
- Adjustment the knob to sets the Min. level, press the button once to save the Min. level. At the same time, the dimmer automatically performs Max. level setting, wait a moment, lights flashes 1 time after all finished, after then returns to normal working mode.

## App Add Dimmer

- Pressing the button 6 times in succession, the light flashes 3 times, indicating that the dimmer enters to distribution networking mode.
- Searching and add the devices in the app, then can be controlled.

## Functionality

